

CROSS REFERENCE CHART FOR LV NH DIN BASES OF VARIOUS MAKES

	Bussmann		GE		SIEMENS		L&T	
SUITABLE FOR	TYPE	AMPS	TYPE	AMPS	TYPE	AMPS	TYPE	AMPS
SIZE C00/000/00	SB 00 - D	160	ISG160	160	3NH3030/3032	160	HB 125	125
SIZE 01/1	SB 1 - D	250	ISG250	250	3NH3230	250	HB 250	250
SIZE 02/2	SB 2 - D	400	ISG400	400	3NH3330	400	HB 800	800
SIZE 03/3	SB 3 - D	630	ISG630	630	3NH3430	630	HB 800	800

CROSS REFERENCE CHART FOR LV BS88 BASES OF VARIOUS MAKES

BS Size	BUSSMANN			GE		SIEMENS		L&T	
	Fuse Types	TYPE	AMPS	TYPE	AMPS	TYPE	AMPS	TYPE	AMPS
Old Type									
F1	NSD / FO6	FA	32	NSH	32			HD32H	32
F1	NSD / FO6	FB	32	NSP	32			HD32P	32
F1	NSD / FO6	FD	32	NSB	32			HD32B	32
A2	HO7 / AAO / FO7	HA	32	SM32H	32			HK32H	32
A2	HO7 / AAO / FO7	HD	32	SM32B	32			HK32B	32
A3	TO7 / BAO / KO7	KA	63	SM63H	63			HK63H	63
A3	TO7 / BAO / KO7	KD	63	SM63B	63			HK63B	63
A4	L14 / CEO / KL14 / M14	LA	125	SM125H	125			HK125H	125
A4	L14 / CEO / KL14 / M14	LD	125	SM125B	125			HK125B	125
New Range - Safe Lock									
F1	NSD / FO6	NNSF	32	SC32H	32	3NW 32 NNSF	32		
F2	ESD	ENSF	63	SC63H	63				
New Range - Cam Master									
A2	HO7 / AAO / FO7	CM32F	32			3NW CM32F9	32		
A3	TO7 / BAO / KO7	CM63F	63			3NW CM63F9	63		
A3C	OSD	CM100F	100			3NW CM100F9	100		

- ▶ The chart is intended for guidance purpose only, considering physical replacability.
- ▶ In identical operating condition, Bussmann fuse can be used to achieve similar performance.
- ▶ Other makes may not necessarily have identical performance. Relevant data like rated voltage, breaking capacity, let thru' current, etc also need to be evaluated while evaluating fuse performance.